



# PVVA.E496340 - Multi-point Interconnection Power Cable Assemblies for Industrial Machinery

## Multi-point Interconnection Power Cable Assemblies for Industrial Machinery

See General Information for Multi-point Interconnection Power Cable Assemblies for Industrial Machinery.

**DONGGUAN FINECABLES CO LTD**

E496340

B5 Blk South Industrial  
Humen Town  
Dongguan, Guangdong 523900 CHINA

**Short-circuit-current Rating**

**Overcurrent Protection**

Model/ Cat. No.	No. of Poles	Con-duc- tor Size, AWG	Cur- rent, A	Volt- age, V	Dis- con- nect Use	Env Rating	IP Rating	Fuse Size — Class/Max Amp Rating						Circuit Breaker Size		SCCR, RMS Sym, kA	Volts Max, V
								J	T	L	RK1	RK5	G	CC	Mfr		

**Male and female power cable fitting**

Male Cable Fitting, Series M12, S Code: Cat. No. MA, followed by 12, followed by M or MS, followed by S, followed by F, P or HD, followed by 03 or 04, followed by ST or RA, followed by any digit of numbers, followed	3-4	16	12	600 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	600 Vac
---	-----	----	----	-------------	----	---	---	---	---	---	---	----	---	---	---	---	---	---	---------

<p>by C or R, followed by B, G, O, Y or P, followed by 125</p> <p>Female Cable Fitting, Series M12, S code: Cat. No. MA, followed by 12, followed by F or FS, followed by S, followed by F, P or HD, followed by 03 or 04, followed by ST or RA, followed by any digit of numbers, followed by C or R, followed by B, G, O, Y or P, followed by 125</p>																			
<p>Male Cable Fitting, Series M12, T Code: Cat. No. MA, followed by 12, followed by M or MS, followed by T, followed</p>	3-4	16	12	60 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	60 Vac

<p>by F, P or HD, followed by 03 or 04, followed by ST or RA, followed by any digit of numbers, followed by C or R, followed by B, G, O, Y or P, followed by 125.</p> <p>Female Cable Fitting, Series M12, T code: Cat. No. MA, followed by 12, followed by F or FS, followed by T, followed by F, P or HD, followed by 03 or 04, followed by ST or RA, followed by any digit of numbers, followed by C or R, followed by B, G, O, Y or P, followed by 125</p>																			
<p>Male Cable Fitting,</p>	5	14	16	63 V ac/dc	No	-	-	-	-	-	-	20	-	-	—	—	—	5	63 Vdc

Series  
M12, L  
Code :  
Cat. No.  
MA,  
followed  
by 12,  
followed  
by MS,  
followed  
by L,  
followed  
by F or  
HD,  
followed  
by 05,  
followed  
by ST,  
followed  
by any  
digit of  
numbers,  
followed  
by C or  
R,  
followed  
by B, G,  
O, Y or P,  
followed  
by 200.

Female  
Cable  
Fitting,  
Series  
M12, L  
code:  
Cat. No.  
MA,  
followed  
by 12,  
followed  
by FS,  
followed  
by L,  
followed  
by F or  
HD,  
followed  
by 05,  
followed  
by ST,  
followed  
by any  
digit of  
numbers,  
followed  
by C or  
R,  
followed  
by B, G,

O, Y or P, followed by 200.																			
-----------------------------------	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

<p>Male Cable Fitting, Series Mini-C: Cat. No. Mini-C, followed by 03 or 04, followed by M, followed by ST or RA, followed by M, followed by any digit of numbers, followed by C or R, followed by B, G, O, Y or P, followed by 200.</p> <p>Female Cable Fitting, Series Mini-C: Cat. No. Mini-C, followed by 03 or 04, followed by F, followed by ST or RA, followed by M, followed by any digit of numbers, followed by C or R, followed by B, G, O, Y or P, followed by 200.</p>	3-4	14	15	300 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	300 Vac
---	-----	----	----	-------------------	----	---	---	---	---	---	---	----	---	---	---	---	---	---	------------

<p>Male Cable Fitting, Series Mini-C: Cat. No. Mini-C, followed by 03 or 04, followed by M, followed by ST or RA, followed by SJF, followed by A or B.</p> <p>Female Cable Fitting, Series Mini-C: Cat. No. Mini-C, followed by 03 or 04, followed by F, followed by ST or RA, followed by SJF, followed by A or B.</p>	3-4	14	15	300 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	300 Vac
---	-----	----	----	-------------------	----	---	---	---	---	---	---	----	---	---	---	---	---	---	------------

<p>Male Cable Fitting, Series Mini-C: Cat. No. Mini-C, followed by 05, followed by M, followed by ST or RA, followed by M, followed by any digit of numbers, followed by C or R, followed by B, G, O, Y or P, followed by 200.</p> <p>Female Cable Fitting, Series Mini-C: Cat. No. Mini-C, followed by 05, followed by F, followed by ST or RA, followed by M, followed by any digit of numbers, followed by C or R, followed by B, G, O, Y or P, followed by 200.</p>	5	14	15	250 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	250 Vac
---	---	----	----	-------------	----	---	---	---	---	---	---	----	---	---	---	---	---	---	---------



Male Cable Fitting, Series Mini-C: Cat. No. Mini-C, followed by 05, followed by M, followed by ST or RA, followed by SJF, followed by A or B.	5	14	15	250 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	250 Vac
Female Cable Fitting, Series Mini-C: Cat. No. Mini-C, followed by 05, followed by F, followed by ST or RA, followed by SJF, followed by A or B																			
<b>Panel-mounted power cable/conductor fitting</b>																			

Series M12, S Code: Cat. No. MB, followed by 12, followed by MS, MB, MC, FS, FB or FC, followed by S, followed by F or R, followed by HD or F, followed by 03 or 04, followed by ST, followed by 2 or 3.	3-4	16	12	600 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	600 Vac
Series M12, T Code: Cat. No. MB, followed by 12, followed by MS, MB, MC, FS, FB or FC, followed by T, followed by F or R, followed by HD or F, followed by 03 or 04, followed by ST, followed by 2 or 3.	3-4	16	12	60 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	60 Vac

Series M12, L Code : Cat. No. MB, followed by 12, followed by MS, MB, MC, FS, FB or FC, followed by L, followed by F or R, followed by HD or F, followed by 05, followed by ST, followed by 2 or 3.	5	14	16	63 V ac/dc	No	-	-	-	-	-	-	20	-	-	—	—	—	5	63 Vdc
Series Mini-C: Cat. No. Mini-C, followed by 03 or 04, followed by M or F, followed by ST, followed by PS, PC or PB, followed by F or R.	3-4	14	15	300 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	300 Vac
Cat. No. Mini-C, followed by 03 or 04, followed by M or F, followed by ST, followed by PS, PC or PB, followed by F or R.				ac/dc															

Series Mini-C: Cat. No. Mini-C, followed by 05, followed by M or F, followed by ST, followed by PS, PC or PB, followed by F or R.	5	14	15	250 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	250 Vac
---	---	----	----	-------------	----	---	---	---	---	---	---	----	---	---	---	---	---	---	---------

**Power Splitter**

<p>Series Mini-C, T type :                  Cat. No. Mini-C, followed by 03 or 04, followed by FMF, followed by T, followed by -M.</p> <p>Cat. No. Mini-C, followed by 03 or 04, followed by MF, followed by T, followed by -M, followed by Mini-C, followed by 03 or 04, followed by F, followed by ST.</p> <p>Cat. No. Mini-C, followed by 03 or 04, followed by FF, followed by T, followed by -M, followed by Mini-C, followed by 03 or 04, followed by M, followed by ST.</p>	3-4	14	15	300 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	5	300 Vac
--	-----	----	----	-------------	----	---	---	---	---	---	---	----	---	---	---	---	---	---------

Series Mini-C, T type: Cat. No. Mini-C, followed by 05, followed by FMF, followed by T, followed by -M.  Cat. No. Mini-C, followed by 05, followed by MF, followed by T, followed by -M, followed by Mini- C, followed by 05, followed by F, followed by ST.  Cat. No. Mini-C, followed by 05, followed by FF, followed by T, followed by -M, followed by Mini- C, followed by 05, followed by M, followed by ST.	5	14	15	250 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	250 Vac
---	---	----	----	-------------------	----	---	---	---	---	---	---	----	---	---	---	---	---	---	------------

Series Mini-C, Y type : Cat. No. Mini-C, followed by 03 or 04, followed by FMF, followed by Y, followed by -M.	3-4	14	15	300 V ac/dc	No	-	-	70	70	70	70	70	70	70	—	—	—	5	300 Vac
Series Mini-C, Y type: Cat. No. Mini-C, followed by 05, followed by FMF, followed by Y, followed by -M.	5	14	15	250 V ac/dc	No	-	-	-	-	-	-	15	-	-	—	—	—	5	250 Vac

Last Updated on 2018-08-01

"© 2022 UL LLC"